



(Pages : 3)

3843 P

Reg. No. :

Name :

VII Semester B.Tech. Examination, July 2009
S7 : Applied Electro and Instrumentation
BIOMEDICAL AND SIGNAL PROCESSING LAB (A)

Time : 3 Hours

Marks : 100

1. Write a Matlab program for simulation of a Digital I.I.R. Butterworth lpf using bilinear transformation for following specification in analog domain.

Passband frequency, $f_p = 2$ Khz

Attenuation at $f_p = 3$ dB

Stopband frequency, $f_s = 5$ Khz

Attenuation at $f_s = 65$ dB

Sampling frequency = 48 Khz

Find the transfer function $H(s)$, $H(z)$ and plot the Magnitude and Phase response of the filter.

2. Write a Matlab program for simulation of a Digital F.I.R. for following specification in analog domain.

Cut-off frequency, $f_p = 2$ Khz

Passband ripple = 0.02

Stopband frequency, $f_s = 4$ Khz

Stopband ripple = 0.02

Sampling frequency = 240 Khz

Window = Kieser Window

Find the order of the filter and plot the Magnitude and Phase response of the filter.

3. Using DSP board write a program for generating 2 KHz Sine wave.
4. Using DSP board write a program for implementing a FIR low pass filter for Cut-off frequency 1 Khz. Sampling frequency 16 Khz.

P.T.O.



5. Using DSP board write a program for implementing a IIR second order Butterworth low pass filter for Cut-off frequency 2 KHz. Sampling frequency 16 KHz.

6. Write a Matlab program for simulation of a Digital I.I.R Butterworth hpf using bilinear transformation for following specification in analog domain.

Passband frequency, $f_p = 5$ KHz

Attenuation at $f_p = 2$ dB

Stopband frequency, $f_s = 2$ KHz

Attenuation at $f_s = 60$ dB

Sampling frequency = 48 KHz

Find the transfer function $H(s)$, $H(z)$ and plot the Magnitude and Phase response of the filter.

7. Write a Matlab program for simulation of a Digital I.I.R. Chebyshev lpf using bilinear transformation for following specification in analog domain.

Passband frequency, $f_p = 1$ KHz

Attenuation at $f_p = 2$ dB

Stopband frequency, $f_s = 5$ KHz

Attenuation at $f_s = 60$ dB

Sampling frequency = 48 KHz

Pass band ripple in dB = 0.5

Find the transfer function $H(s)$, $H(z)$ and plot the Magnitude and Phase response of the filter.

8. Using DSP board write a program for implementing a FIR high pass filter for Cut-off frequency 2 KHz. Sampling frequency 16 KHz.

9. Using DSP board write a program for implementing a IIR second order Chebyshev high pass filter for Cut-off frequency 1 KHz. Sampling frequency 16 KHz.



10. Write a Matlab program for simulation of a Digital FIR band pass filter of length 41 for meeting following specification in analog domain.

Order of the filter $N = 41$

Sampling frequency = 48 KHz

Lower cut-off frequency = 1 KHz

Upper cut-off frequency = 2 KHz

Use rectangular window.

Plot impulse response $h(n)$ and magnitude and phase response of the filter.

11. Write a Matlab program for simulation of a Digital FIR band stop filter of length 41 for meeting following specification in analog domain.

Order of the filter $N = 41$

Sampling frequency = 48 KHz

Lower cut-off frequency = 1 KHz

Upper cut-off frequency = 2 KHz

Use rectangular window.

Plot impulse response $h(n)$ and magnitude and phase response of the filter.

12. Setup a Bio Potential Amplifier.

13. Setup a circuit for respiratory rate measurement.

14. Setup and plot ECG waveforms.

15. Using Cardimate, measure ECG parameters.
